



| ITEM | DESCRIPTION | ITEM | DESCRIPTION |
|------|----------------------|------|----------------------------|
| R1 | 22,000 OHM 1/2 WATT | R21 | 2.2 MEG OHM 1/2 WATT |
| R2 | 10,000 OHM 1 WATT | R22 | 220,000 OHM 1/2 WATT |
| R3 | 2.5 MEG OHM 1/2 WATT | R23 | 200,000 OHM 1/2 WATT |
| R4 | 100,000 OHM 1/2 WATT | R24 | 100,000 OHM 1/2 WATT |
| R5 | 100,000 OHM 1/2 WATT | R25 | 270 OHM 1 WATT |
| R6 | 470,000 OHM 1/2 WATT | R26 | 4700 OHM 1/2 WATT |
| R7 | 10 MEG OHM 1/2 WATT | R27 | 47,000 OHM 1 WATT |
| R8 | 220,000 OHM 1/2 WATT | C1 | 50 MMF 400 VOLT CONDENSER |
| R9 | 100,000 OHM 1/2 WATT | C2 | .05 MFD 200 VOLT CONDENSER |
| R10 | 4700 OHM 1/2 WATT | C3 | .05 MFD 400 VOLT CONDENSER |
| R11 | 4700 OHM 2 WATT | C4 | .05 MFD 400 VOLT CONDENSER |
| R12 | 220,000 OHM 1/2 WATT | C5 | 170 MMF 400 VOLT CONDENSER |
| R13 | 470,000 OHM 1/2 WATT | C6 | .01 MFD 400 VOLT CONDENSER |
| R14 | 1500 OHM 1 WATT | C7 | 500 MMF 400 VOLT CONDENSER |
| R15 | 1 MEG OHM 1/2 WATT | C8 | .02 MFD 400 VOLT CONDENSER |
| R16 | 10,000 OHM 1 WATT | C9 | .01 MFD 400 VOLT CONDENSER |
| R17 | 100,000 OHM 1/2 WATT | C10 | .01 MFD 400 VOLT CONDENSER |
| R18 | 470,000 OHM 1/2 WATT | C11 | 10 MFD 350 VOLT CONDENSER |
| R19 | 10 MEG OHM 1/2 WATT | | |
| R20 | 470,000 OHM 1/2 WATT | | |

| ITEM | DESCRIPTION |
|------|----------------------------------|
| C12 | 10 MFD 350 VOLT CONDENSER |
| C13 | DUAL 30 MFD 350 VOLT CONDENSER |
| C14 | 1 MFD 400 VOLT CONDENSER |
| C15 | 1 MFD 400 VOLT CONDENSER |
| C16 | MICA CONDENSER .003 MFD 400 VOLT |
| C17 | 1 MFD 400 VOLT CONDENSER |
| C18 | .01 MFD 400 VOLT CONDENSER |
| C19 | .001 MFD 400 VOLT CONDENSER |
| C20 | .01 MFD 400 VOLT CONDENSER |
| C21 | .01 MFD 400 VOLT CONDENSER |
| C22 | 1 MFD 400 VOLT CONDENSER |
| C23 | 20 MFD 25 VOLT CONDENSER |
| C24 | 20 MFD 25 VOLT CONDENSER |
| C25 | 3 MMF CONDENSER |
| C26 | MICA CONDENSER .003 MFD |

| ITEM | DESCRIPTION |
|------|-----------------------------|
| M1 | LOOP ANTENNA |
| M2 | OSC. COIL 455 KC |
| M3 | IF TRANSFORMER 455 KC |
| M4 | IF TRANSFORMER 455 KC |
| M5 | 50,000 OHM TONE CONTROL |
| M6 | PHONO JACK |
| M7 | F. M. JACK |
| M8 | EXT. AMP. JACK |
| M9 | 500,000 OHM VOLUME CONTROL |
| M10 | 200 OHM 60 MA CHOKE |
| M11 | POWER TRANSFORMER |
| M12 | 15 AMP FUSE |
| M13 | LAMP |
| M14 | MOTOR SWITCH |
| M15 | RECORDING MOTOR |
| M16 | 5000 OHM OUTPUT TRANSFORMER |
| M17 | EXT. SPEAKER JACK |
| M18 | SPEAKER (3.2 VOICE COIL) |
| M19 | MIC. JACK |
| M20 | RECORDER SWITCH |
| M21 | RECORDING HEAD PLUG |
| M22 | N.E. 51 NEON LIGHT |
| M23 | RADIO PHONO. MIC. SWITCH |
| M24 | RECORD-LISTEN SWITCH |
| M25 | 30-40 KC OBC COIL |

